



## TECHNICAL SPECIFICATIONS

|                       |  |                              |   |
|-----------------------|--|------------------------------|---|
| <b>Operation</b>      | Controlled or control-free entrance/exit in both directions  | <b>Safety Level Setting</b>  | With 4 security levels that can be defined as desired by the customer, turnstile is able to detect unauthorized passes and passes in the opposite direction and prevents or notifies, with audio or discreetly. |
| <b>Chassis</b>        | AISI 304 quality stainless steel. Optional: Black, stainless steel   | <b>Indicator</b>             | LED illumination around the upper cover and passage LEDs on the upper table. Optional: LED lighting on wings.   |
| <b>Wing</b>           | With high glass, linear winged, 10 mm tempered glass; Optional: Smoke Colored Glass, Height: 170 cm.   | <b>Operating Voltage</b>     | 110-230 VAC, 47-60 Hz   |
| <b>Upper Table</b>    | Optional: 130 cm / 150 cm  | <b>Power Consumption</b>     | 120 W during passage, 10 W during standby (for two wings)   |
| <b>Functions</b>      | 10 mm black tempered glass. Optional: Wood   | <b>Operating Temperature</b> | -10° / +70°   |
| <b>Mechanism</b>      | Works bidirectionally and allows the passage of a single person only with its microprocessor control, electronic passage memory feature saves in memory card swipes that occur before a passage is completed and allows them to pass without closing the wings. Optional: 2 x RS232 and 1 x RS485 communication ports. | <b>Passage Speed</b>         | ~40 persons/minute  |
| <b>Sensors</b>        | With its adjustable mechanical torque control, the unit does not cause injury in the event of any jamming.   | <b>Passage Width</b>         | 56 cm   |
| <b>Emergency Mode</b> | 8 reciprocal sensors in every corridor   | <b>Weight</b>                | ~148 kg (Single Wing)   |
|                       | Turnstile switches to emergency mode upon the receipt of a signal from fire detection system and wings open. In case of power shortage, wings automatically switch to open position with the power supplied from the accumulator (fail safe).  | <b>Security Level</b>        | High Security   |
|                       |  | <b>Areas of Use</b>          | Suitable for indoor use   |
|                       |  | <b>Accessories</b>           | Logo Engraving, Sticker, Remote Control Unit, Stainless Steel Reader Apparatus, Meter, Button Control Unit, Stainless Steel Reader Leg, Stainless Steel Bottom Plate  |

